

Programming the Midland WR-300 Weather Radio

1. Insert 4 AA batteries in the battery compartment before you plug in the electrical adaptor.

It is important to have good batteries in the radio at all times in case there is a loss of power. The radio will give you an indication when the batteries are low.



2. Set the Alert Type
 - a. Press and release the "MENU" button.
 - b. Press the "UP" arrow until "ALERT MODE" is displayed.
 - c. Press the "SELECT" button.
 - d. Use the "UP" or "DOWN" arrow to "VOICE".
 - e. Press the "SELECT" button to save setting.
3. Set the Weather Channel
 - a. Press and release the "MENU" button (skip if already in MENU).
 - b. Press the "UP" arrow until "WEATHER CHANNEL" is displayed.
 - c. Press the "SELECT" button.
 - d. Use the "UP" arrow to scroll to desired channel (7 for Story & Boone counties).
 - e. Press the "SELECT" button to save channel.
4. Add County Federal Information Processing System (FIPS) Codes
 - a. Press and release the "MENU" button (skip if already in MENU).
 - b. Press the "UP" or "DOWN" arrow until "COUNTY CODE" is displayed.
 - c. Press the "SELECT" button.
 - d. Press the "UP" arrow to "MULTIPLE" and press "SELECT".
 - e. "CODE 01" should be displayed; press "SELECT".
 - f. Use the "UP" or "DOWN" arrow to set first digit of county code (019169 for Story).
 - g. Press the "RIGHT" arrow to go to next digit in the FIPS; repeat for all 6 digits.
 - h. Press the "SELECT" button to store the FIPS number.
 - i. Press the "UP" arrow to "CODE 02" to add a second county code (019015 for Boone) and repeat steps f-h.
 - j. If you want to add more counties, additional codes are listed on the back of these instructions.
5. Set the Date
 - a. Press and release the "MENU" button (skip if already in MENU).
 - b. Press the "UP" arrow until "SET UP DATE" is displayed.
 - c. Press the "SELECT" button and the day setting should begin flashing.
 - d. Use the "UP" or "DOWN" arrow to adjust the day setting.
 - e. Press the "RIGHT" arrow to set the month; use "UP" or "DOWN" arrow to adjust the month.
 - f. Press the "RIGHT" arrow to set the year; use "UP" or "DOWN" arrow to adjust the year.
 - g. Press the "SELECT" button to store the date setting.
6. Set the Time
 - a. Press and release the "MENU" button (skip if already in MENU).
 - b. Press the "UP" arrow until "SET UP TIME" is displayed.
 - c. Press the "SELECT" button and the hour setting should begin flashing.
 - d. Use the "UP" or "DOWN" arrow to adjust the hour setting.
 - e. Press the "RIGHT" arrow to set the minutes.
 - f. Use the "UP" or "DOWN" arrow to adjust the minute setting.
 - g. Press the "SELECT" button to store the time setting.

Make sure volume button (on side) is in "ON" position and you are ready to go!

Reviewed 2019

Federal Information Processing System (FIPS) Codes for Iowa

Adair	019001	Floyd	019067	Monona	019133
Adams	019003	Franklin	019069	Monroe	019135
Allamakee	019005	Fremont	019071	Montgomery	019137
Appanoose	019007	Greene	019073	Muscatine	019139
Audubon	019009	Grundy	019075	O'Brien	019141
Benton	019011	Guthrie	019077	Osceola	019143
Blackhawk	019013	Hamilton	019079	Page	019145
Boone	019015	Hancock	019081	Palo Alto	019147
Bremer	019017	Hardin	019083	Plymouth	019149
Buchanan	019019	Harrison	019085	Pocahontas	019151
Buena Vista	019021	Henry	019087	Polk	019153
Butler	019023	Howard	019089	Pottawattamie	019155
Calhoun	019025	Humboldt	019091	Poweshiek	019157
Carroll	019027	Ida	019093	Ringgold	019159
Cass	019029	Iowa	019095	Sac	019161
Cedar	019031	Jackson	019097	Scott	019163
Cerro Gordo	019033	Jasper	019099	Shelby	019165
Cherokee	019035	Jefferson	019101	Sioux	019167
Chickasaw	019037	Johnson	019103	Story	019169
Clark	019039	Jones	019105	Tama	019171
Clay	019041	Keokuk	019107	Taylor	019173
Clayton	019043	Kossuth	019109	Union	019175
Clinton	019045	Lee	019111	Van Buren	019177
Crawford	019047	Linn	019113	Wapello	019179
Dallas	019049	Louisa	019115	Warren	019181
Davis	019051	Lucas	019117	Washington	019183
Decatur	019053	Lyon	019119	Wayne	019185
Delaware	019055	Madison	019121	Webster	019187
Des Moines	019057	Mahaska	019123	Winnebago	019189
Dickinson	019059	Marion	019125	Winneshiek	019191
Dubuque	019061	Marshall	019127	Woodbury	019193
Emmet	019063	Mills	019129	Worth	019195
Fayette	019065	Mitchell	019131	Wright	019197

Channel 1 162.400 for Humboldt, Webster

Channel 7 162.550 for Boone, Greene, Dallas, Carroll, Story